

ATC-1000S Upgrade

- Administrator
- Authentication Configuration
- System IP Configuration
- System Status
- Load default setting
- Firmware update**
- Boot Loader upgrade
- TCP Mode
- UDP Mode
- UART
- SMTP
- ADC
- DIDO
- Reset Device

System Status

Kernel Version	V1.44.3.10 2017/06/29
MAC Address	00:11:22:54:95:7D
Nickname	<input type="text" value="NetUART"/> <input type="button" value="Update"/>

Note:

Comment name only can use "0-9", "a-z", "A-Z", "_", "-"

选择此选项进行固件升级

Select this option to upgrade the firmware.

- Administrator
- Authentication Configuration
- System IP Configuration
- System Status
- Load default setting
- Firmware update**
- Boot Loader upgrade
- TCP Mode
- UDP Mode
- UART

Firmware Update	
Please input the password to continue the Firmware Update process.	
Password	<input type="password" value="....."/> 默认密码是system
ReConfirm	<input type="password" value="....."/> Default Password: system
<input type="button" value="Update"/>	

Notice:

After clicking the "UPDATE" button, if the firmware update webpage is not redirected correctly or is shown as "Webpagenot found". Please connect to <http://192.168.1.190>

Then will appear the Erase Flash interface:

Erase Flash (64/128)

If this webpage doesn't refresh smoothly, please connect to <http://192.168.1.190> to continue.

F/W	
Select the image file:	<input type="text"/> <input type="button" value="浏览..."/> Find the upgrade file: flash_512.bin
<input type="button" value="UPDATE"/>	
http://192.168.1.190	

点击浏览，找到升级文件，
.bin属性的文件

flash_1M.bin	2017/6/29 星期...	KuaiZipMount.bin	1,024 KB
flash_2M.bin	2017/6/29 星期...	KuaiZipMount.bin	2,048 KB
flash_512.bin	2017/6/29 星期...	KuaiZipMount.bin	512 KB
flash_app.bin	2017/6/29 星期...	KuaiZipMount.bin	512 KB
OTP_64k.bin	2017/6/29 星期...	KuaiZipMount.bin	64 KB
OTP_CLI_64k.bin	2017/6/29 星期...	KuaiZipMount.bin	64 KB

F/W

Select the image file:

D:\文件备份\F盘\Support\ATC-1000问题\exe_ATC_Net-UART144.3.10 浏览...

UPDATE 点击UPDATE按钮 Click the update button

<http://192.168.1.190>

Uploading>>>>>

出现Uploading>>>>表示正在升级

Uploading In progress...

OK!

2

OK!

Continue

升级完成点击 Continue 即可。Click Continue to complete the upgrade.

固件升级之后会重新跳出登录窗口，内部设置参数不会恢复出厂默认设置。

After the firmware upgrade, the login window will jump back, and the internal settings parameters will not revert to the factory default settings.